

# Refit Solutions from GE



Application illustration only, subject lamps not used in photo.



## Ballast Bypass LED U-Tubes (Type B)

Convert your existing fluorescent fixture to LED lighting without needing a comprehensive reinstall. LED tubes are ideal for those seeking high energy savings with minimal installation time. The existing fixture is wired to bypass the ballast, which further reduces energy use and eliminates the need to check ballast compatibility. Additional maintenance savings are realized by removing costs associated with replacing ballasts.

### FEATURES

- T8 U-Tube 1-5/8" and 6" spacing
- 13 Watts
- 1750 - 1900 lumens
- Available in 3000K, 3500K, 4000K and 5000K
- 50,000 hour rated life
- Open or enclosed fixtures
- 5 year limited warranty

### REQUIREMENTS

- Non-shunted sockets
- In-line fuse

### BENEFITS

- Fast and easy LED upgrade
- Low energy LFL replacement
- 2X longer life than LFL (50,000 vs. 24,000 hours)
- Better quality of light  
-instant on
- Easy disposal, non-hazardous waste
- Additional Cost Savings- ballast bypass wiring eliminates ballast replacement costs

## GE LED U-Tubes Type B

Type	Base Type	Watts	Order Code	Description	Volts	Case Qty**	MOL (In)	Lumens Initial	Initial Color Temp	CRI	Wattage Replacement	*Rated Life L70 (Hrs)	Power Factor	DLC ©	UL	#Location Rating	Additional Information
<b>Ballast Bypass Type B LED U6-Tubes</b>																	
T8	2G13	13	34480	LED13BT8/U6/830	120-277	20	22.5	1800	3000K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
	2G13	13	34481	LED13BT8/U6/835	120-277	20	22.5	1850	3500K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
	2G13	13	34482	LED13BT8/U6/840	120-277	20	22.5	1900	4000K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
	2G13	13	34484	LED13BT8/U6/850	120-277	20	22.5	1900	5000K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
<b>Ballast Bypass Type B LED U1-5/8-Tubes</b>																	
	2G13	13	34487	LED13BT8/UJ/830	120-277	20	22.5	1750	3000K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
	2G13	13	34489	LED13BT8/UJ/835	120-277	20	22.5	1800	3500K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required
	2G13	13	34499	LED13BT8/UJ/840	120-277	20	22.5	1850	4000K	80+		50,000	>.9	Yes	Yes	Damp	Single-ended, In-line fuse Required

## In-Line Fuse & Socket Kit

Order Code	Description	Kit Contents
32075	BT8-2L-KIT/NS	1 Fuse (1A), 2 Pre-wired sockets, Prewired quick disconnect.
32083	BT8-3L-KIT/NS	1 Fuse (1A), 3 Pre-wired sockets, Prewired quick disconnect.
32084	BT8-4L-KIT/NS	1 Fuse (1A), 4 Pre-wired sockets, Prewired quick disconnect.

\* For use with single ended 120-277 volt powered LED Tubes

To learn more about saving money and energy, go to: <http://products.currentbyge.com>.



**current**  
powered by GE

<http://products.currentbyge.com>.

GE and the GE Monogram are trademarks of the General Electric Company. All other trademarks are the property of their respective owners. Information provided is subject to change without notice. All values are design or typical values when measured under laboratory conditions. GE Lighting and GE Lighting Solutions, LLC are businesses of the General Electric Company. © 2018 GE.

LEDL059 (Rev 05/24/18)

