

CL SERIES INSTALLATION INSTRUCTIONS

Materials Required by Contractor:

- 90°C rated supply conductors
- Silicone Sealant Caulk
- 5/32 hex key

Before Starting Work:

- Ensure that all electrical connections are not live! Take all steps necessary to make sure that electrical connections will not become live accidentally during installation.

Installation Steps:

1. Remove 4 screws that attach lens to fixture housing.
2. Remove 4 screws that attach reflector to fixture housing. LEDs and electrical components will now be exposed. Use caution and avoid touching the LEDs as it may damage the light fixture. Place the reflector aside.
3. Mount the fixture housing. Depending on the installation, the housing can be installed over an existing junction box or it can be surface mounted. Conduit can be brought in through the top of the housing or through the knock-outs on the side of the housing. Bring supply wires into the housing. Use silicone to seal any holes that were drilled into the fixture housing. Be sure to reinstall plugs into any unused knockouts.
4. Hold LED panel fixture housing and make electrical connections. Use 90°C rated supply conductors.

| |
|------------------------|
| Black = Live |
| White = Neutral |
| Green = Ground |

5. Reattach the reflector to the fixture housing using four original screws.
6. Reinstall lens with four original screws.

